



# CHANNEL VISION™

## P-6014 CAT5 Camera Sequencer

Channel Vision's **P-6014** is a 4-input, 2-output CAT5 Camera Sequencer and Switcher for Channel Vision's 6210 Color CAT5 Cameras (sold separately) and 3112 CAT5 Camera Breakout for standard cameras (sold separately). Easily view all system cameras through the auto-sequencer or via push-button on the optional remote control. Separate video homing module available for automatic video switching when triggered by an external system such as Channel Vision's telephone entry, CAT5 intercom, or any 3rd party dry contact closure.

The RS-232 interface and AV loop out connections make it easy to integrate the P-6014 into any security system - from the most basic to the most advanced touchscreen-driven systems on the market.

# P-6014



### Features:

- Creates an easy interface for CAT5 cameras
- Switches both audio and video
- Monitor output sequences through the camera views automatically
- Easily adjustable dwell time
- Offers IR and Serial control options
- Mounts in a structured wire enclosure
- Cost-effective and easy-to-install

### \*Specifications: (typical @25° C)

#### P-6014

<b>Dimensions:</b>	5.5"W x 6.5"H x 1.5"D
<b>Power Supply:</b>	15VDC @ 1.6A
<b>IR Frequency Range:</b>	30-60kHz
<b>Operating Temp:</b>	-10°C to 50°C
<b>Audio Bandwidth:</b>	20Hz - 20kHz
<b>Video Crosstalk:</b>	-80dB
<b>Video Bandwidth:</b>	DC - 20MHz
<b>Video Crosstalk:</b>	-60dB
<b>CAT5 Ports:</b>	
<b>Max run length:</b>	250ft (Camera input + Monitor output)
<b>Max Camera Power:</b>	12VDC @ 280mA

\*Specifications subject to change without notice.



# CHANNEL VISION™

234 FISCHER AVENUE • COSTA MESA, CA 92626 USA  
(714) 424-6500 □ (800) 840-0288 □ (714) 424-6510 fax  
www.channelvision.com □ email: sales@channelvision.com